

## Compatibility Information



### MINI Receiver 24V or 230V

Art.-Nr. 24V: B43A224061

Art.-Nr. 230V: B43A224071

433MHz, AM, rollender Code

An external receiver is only required, when an other item but a Seip Garage Door Operator shall be controlled by a Seip hand transmitter (e.g. a sliding gate operator, a door operator of another make or external lights).

Component	Compatibility
Door Operators	The receiver can be connected to any door operator providing a push button connector. The 24V or 230V power supply can be either taken from the operator or from an external source. The receiver is based on 4-wire system - two impulse cables (for the push button connectors) and two power supply cables. If required, the receiver can also be configured to suite a 3-wire system.
Hand Transmitters	All Type SKR433 hand transmitters: MIDI Transmitter SKR433-1 MINI Transmitter SKRJ433
Other sending devices	All Type SKR433 sending devices: Digi Pad Type SKR433 / SKR4C433 Remote Wall Push Button, Type SKR433 / SKR2W433
Maximum Number of Devices	A maximum of 15 devices (hand transmitter, remote wall push-button, digital pad) can be programmed with the MINI receiver. If more than 15 devices are programmed to the receiver, then one of the previously programmed devices will be substituted by the latest programmed device.
HomeLink	MINI receivers from software version "DMCG1V1" are compatible with HomeLink (from Revision 6). MINI receivers with this latest software are available from Juli 2005 approx.. MINI receivers with an older software version are NOT compatible to HomeLink. Please inform your dealer in advance, when you intend to use a MINI receiver with a HomeLink system.